

DESCRIPTION

The BC-5000-12 is a dedicated battery charger for the WM-5225 and WM-5265 Wireless Microphones, WM-5325 Wireless Transmitter, and WT-5100 Portable Receiver, which work with AD-5000-6. It employs a quick charging system for nickel metal hydride (Ni-MH) batteries, allowing up to 12 wireless microphones to be fully charged within 3 hours.

SPECIFICATIONS

| | |
|---|---|
| Power Source | 12 V DC (optional AC adapter AD-5000-6 must be used) |
| Power Consumption | 4.4 A |
| Charging Time | Max. 3 h |
| Number of Wireless Microphones to be Charged Simultaneously | 12 pieces |
| Operating Temperature | 0 °C to +40 °C (32 °F to 104 °F) |
| Operating Humidity | 30 % to 85 %RH (no condensation) |
| Finish | Case: Steel plate, black, paint Microphone receptacle section: ABS resin, black |
| Dimensions | 390 (W) × 118 (H) × 246 (D) mm (15.35" × 4.65" × 9.69") (including mounting adapter) |
| Weight | 3.4 kg (7.5 lb) (charger with the mounting adapters attached) |
| Accessory | Mounting adapter ...12 |
| Option | Rechargeable battery: WB-2000-2 (containing 2 pieces) AC adapter: AD-5000-6 |

APPEARANCE

